

PRODUCT DETAILS

Pollak

Pollak

Pollak



Pollak

Pollak

Pollak

31-196V

Ignition Starter Switch

Retail Visi/Pak Clamshell

Pollak

Part Specifications

Voltage: 14 Volt

Amperage 30 amps Continuous; Ignition

Rating: Terminal 8 amps; Accessory
Terminal 30 amps (Inductive); Start
Terminal 75 amps Make 20 amps
Break

Functions: ACC,OFF,ON/ACC,Start

POP: F
Per Car: 1

CHECK YOUR FIT

✚ Add to Saved List

Number of Switch Positions: 4
Terminal Quantity: 4
Terminal Gender: Male (1)
Terminal Type: Std
Mounting Type: Screw
Hardware included: Yes
Warranty: 1 year
Base Type: 1
Coding: Universal
Housing Material: Zinc Die-Cast
Integral Lock Cylinder: No
Key logo: Pollak
Key Quantity: 2
Keys Included: Yes
M/H/P: 4
Number of Lip Seals: 1
Starter Lockout: No

Features & Benefits

Pollak has been providing innovative designs and high-quality parts to the OEM and Aftermarket Heavy Truck, Off-Road, RV, Marine, Industrial, and Towing Industries since 1909.

- One Piece Zinc Die-Cast Housing
- Solid Copper Contacts
- Brass Terminals
- Weather resistant seals
- Internally Lubricated

For Catalog assistance: (718) 316-4400

[Back to Top](#)
